

RAVE SL-3456 Rotating LED Mini Light  
DMX Channels

Channel	Function	Value	Description
1	Strobe	0-5	Off
		6-255	Strobe
2	Red/Pink Control	0	Off
		1-255	Dimmer
3	Green/Orange Control	0	Off
		1-255	Dimmer
4	Blue/White Control	0	Off
		1-255	Dimmer
5	Rotation	0-5	Stop
		6-127	Forward
		128-255	Reverse
6	Command	0-5	Manual
		6-250	Automatic
		250-255	Sound Control